


## SEQUENCE OF OPERATION:



## LIGHT FIXTURES:

- All fixtures are dimmable;
- Max. and Min. Trim can be set via App;

## OCCUPANCY CONTROL:

- Fixtures automatically go to set brightness when space is occupied;
- Fixtures automatically turn off or low level when space is vacant;
- Occupancy or Vacancy mode;
- Brightness level for Occupied and Vacant state, delays and transitions can be set via App;

## DAYLIGHT CONTROL:

- Smooth and continuous dimming;
- Delays, transitions and light harvesting sensitivity can be set via App;

## PLUG LOAD CONTROL:

- Receptacle automatically turns ON/OFF with motion sensor and/or schedule

## MANUAL CONTROL:

- ON/OFF, dim up and down, select scene












## TIME SCHEDULE:

- Time, recurring day of the week schedules, yearly special day schedules can be set via App;

## ADDITIONAL OPTIONS:

- Shade control;
- GPS Time-keeper for clock accuracy;
- Gateway for clock accuracy, remote assistance, energy and space utilization analytics, BMS integration, voice activated commands
- Emergency Lighting Control

## LEGEND

	LINE VOLTAGE
	0-10V
	LOW VOLTAGE
	TO MAIN POWER
	0-10V DOWNLIGHT
	0-10V LINEAR PENDANT
	OCCUPANCY SENSOR
	KEYPAD SWITCH
	BLUETOOTH MESH
	CONTROLLER
	5W TRANSFORMER

## BILL OF MATERIAL

QTY	PRODUCT#	DESCRIPTION
4	C-T20-17-DJ00	0-10V/PLUG LOAD CONTROLLER
1	S-OP-012-DTWH	OCCUPANCY SENSOR
1	S-DL-012-DTWH	DAYLIGHT SENSOR
1	K-Q4-UDL-00WH	KEYPAD - Q SERIES - 4 BUTTONS WHITE
1	A-T05-12-17-DJ00	5W TRANSFORMER
	BY OTHERS:	
12	0-10V DOWNLIGHT	0-10V DIMMING
1	0-10V LINEAR PENDANT	0-10V DIMMING