

## Designer Keypad Interface K-ZC-WDW-000



### Certifications



### Installation

The KZC can be installed inside the j-box behind the third party keypad as well as remote. The device requires 12-24VDC. It can be powered by a BubblyNet controller with auxiliary output as well as a small transformer.

For installation on single-gang j-boxes with line voltage wire, do not use shallow boxes. For regular depth, avoid splices inside the box (just 1 line to the box). For other configurations, use multigang, 4x4 with switch ring.

### Connectivity

Devices are repeaters for other devices and should be installed within a certain maximum distance from each other.

Typical maximum distance:

<u>Outdoor (line of sight):</u>	200ft
<u>Indoor (through building material):</u>	
Glass:	100ft
Drywall:	70ft
Cinderblock:	60ft
Brick:	50ft
Concrete + rebar	0ft

For design purposes a 60ft. maximum distance is appropriate for most installations.

### Description

The Designer Keypad Interface is a wireless device that can be configured by the BubblyNet App. It allows to connect up to 4 analog (0-10V) inputs and 4 close contacts inputs thus converting third party keypads, dimmers and switches into smart wireless user interfaces.

### Features

- Wireless, Bluetooth Mesh
- Battery-operated (CR2032 Battery)
- Protection Grade: IP 20
- Connect to up to 8 Inputs (Buttons)
- Easy Reconfiguration with the use of the BubblyNet App
- Smooth Dimming, Recall Animations and Control and Recall Scenes.
- Dimensions: 1.73" x 2.24" x 0.75" (44mm x 57mm x 19mm)

### Applications

The BubblyNet App configures toggle switches, momentary/push buttons and rotary dimmers on the 4 +4 inputs so as to toggle ON/OFF, Dim up and down, recall scenes and presets as well as control motorized shades. The KZC allows to control all luminaires types supported by BubblyNet such as Forward and Reverse Phase, 0-10V, DALI and DMX.

Examples of pushbuttons to be used in conjunction with the K-ZC-WDW-000:



